

USB Stick Modem

Model ICOMDM-GSMUA

Features

- ◆ Standard USB Connector, Supports USB 2.0+
- ◆ Internal Antenna Integrated
- ◆ External antenna port
- ◆ SIM card behind back cover
- ◆ Once connected, modem can swivel 180 degrees
- ◆ Small size - 1.1" x 3.2" x 0.5"
- ◆ Connection Lights on front and back
- ◆ One year warranty



Specifications

| | |
|---------------------------|---|
| Memory | Micro SD up to 32 GB supported |
| Cellular Protocol | EDGE, GSM, GPRS, HSPA+UMTS, HSPA+ |
| Max Download Speed | 21.6 Mbps |
| Max Upload Speed | 5.76 Mbps |
| Size | 1.1" x 3.2" x 0.5" (27.94mm x 81.28mm x 12.7mm) |
| Bands Supported | 2G: 850, 900, 1800, 1900 MHz 3G/4G: 1700/2100 (AWS) |
| Weight | 1.1 oz |
| Dimensions | 69 x 26.5 x 12mm (1.1" x 3.2" x 0.5") |
| Temperature | Operating: -10 ~ 55oC Storage: -20 ~ 60oC |

Connector Lights

| Light | Status |
|--------------------------------------|--|
| Blinking green twice every 3 seconds | Data stick is powered on |
| Blinking green once every 3 seconds | EDGE registration |
| Blinking blue once every 3 seconds | 3G registration |
| Blinking red | Data stick is powered on & searching for the SIM card |
| Solid red | Data stick powered on & searching for available network (EDGE, 3G) |
| Solid Green | Established EDGE connection |
| Solid blue | Established 3G connection |
| Off | No power |

Liquid Damage Indicators (LDI)

The device includes an indicator that shows if it has been damaged by water or other liquid, thereby voiding the warranty. To view the Liquid Damage Indicator (LDI), remove the cover from your device.

White LDI
(Indicates no damage)



Red LDI
(Indicates damage)



Subscriber Identity Module (SIM) Card

Your SIM card identifies you to the wireless network. You will not be able to connect to the network without your SIM card.

- ◆ To Insert SIM Card, follow these steps
 1. Remove back cover
 2. Insert SIM card into SIM card slot
 3. Replace back cover
- ◆ To remove SIM Card, follow these steps
 1. Remove back cover
 2. Slide SIM card out of SIM card slot
 3. Replace back cover